



LOCATION		DATE
PREPARED BY		QUANTITY
COMMENTS		FIXTURE TYPE
CATALOG NUMBER		

## Cirrus LED Flush Mount C2F Series

### Features

A round floating cloud style with a white diffuser.  
Ideal use in kitchens, hallways, and anywhere general lighting is needed.  
Provides lighting in residential, commercial and hospitality applications.  
Fixture mounts to standard junction box (not included).



### Emergency Back-Up (Optional '-BB')

- 90 minute run-time
- 7.4V 2500 mAh Lithium Ion Battery
- 8 watts

### Construction

A 22-gauge steel housing made by stamping process and painted in lighting grade white to provide long lasting finish with 3 side white screws to hold molded diffuser. Standard mounting holes and hardware included. Power supply connections must be made inside a junction box (not included).

### Finish

White finish.

### Diffuser

0.070" thick smooth white acrylic.

### Electrical

Input 120VAC / 60 Hz.  
Compatible with TRIAC and ELV dimmers.

### LED

Integrated LED modules capable of producing:  
17W = 1258 delivered lumens  
27W = 1600 delivered lumens  
35W = 2236 delivered lumens  
Adjustable Choice 2700K, 3000K, 3500K, 4000K, 5000K (CCT).  
Rated for 50,000 Hrs. 90 CRI.

### Certification

All fixtures are cETLus listed for indoor damp locations.  
ENERGY STAR® qualified.  
T24-JA8 Compliant.  
Suitable for use in clothes closets when installed in accordance with the NEC 410.16 spacing requirements.

### Warranty

Limited warranty: This fixture is free from defects in materials and workmanship for a period of 5 years from date of purchase.

**Specifications and dimensions**  
subject to change without notice.

## Ordering Information:

White	LED	Delivered Lumens	Adjustable CCT	DIA.	D
C2F11600L5AJD1	17W	1258	2700K/3000K/3500K/4000K/5000K	11"	3"
C2F142400L5AJD1	27W	1600	2700K/3000K/3500K/4000K/5000K	14"	3"
C2F142400L5AJD1-BB	27W	1600	2700K/3000K/3500K/4000K/5000K	14"	3"
C2F193100L5AJD1	35W	2236	2700K/3000K/3500K/4000K/5000K	19"	3"
C2F193100L5AJD1-BB	35W	2236	2700K/3000K/3500K/4000K/5000K	19"	3"



FLUSH MOUNT



BATTERY BACKUP