



LED Adjustable Color Retrofit Kit RFKIT9AJ, RFKIT13AJ, RFKIT14AJ

Features

Convert your existing fluorescent into an energy saving LED fixture.
Easy installation with minimal cutting and magnetic mounting.
Lasts up to 5 times longer than fluorescent. Replaces ceiling and wall lamps. Adjustable color 3000K warm white or 4000K cool white.

Construction

Aluminum base mounting magnets and hardware are included.
Power supply connections can be made inside fixture.

Electrical

This unit is direct wired with constant current low voltage electronic LED drivers.
The constant current LED driver is rated for 120-277V multi-volt.
For indoor applications.

Lamping

9W LED module producing 992 source lumens (replaces 13W compact fluorescent)
13W LED module producing 1398 source lumens (replaces 18W compact fluorescent)
14W LED module producing 1679 source lumens (replaces 26W compact fluorescent)
Rated for 50,000 hrs. 3000K/4000K adjustable warm to cool color

Certification

All fixtures are cETLus listed for damp locations.

Warranty


Limited warranty: This fixture is free from defects in materials and workmanship for a period of 5 years from date of purchase.

Specifications and dimensions
subject to change without notice.


LOCATION		DATE
PREPARED BY		QUANTITY
COMMENTS		FIXTURE TYPE
CATALOG NUMBER		




RFKIT9AJ



RFKIT13AJ



RFKIT14AJ



Ordering Information:

White	LED	Source Lumens	CCT	L x W (LED Board)
RFKIT9AJ	9W	992	3000K/4000K	6.3" x 2.6"
RFKIT13AJ	13W	1398	3000K/4000K	11" x 1.45"
RFKIT14AJ	14W	1679	3000K/4000K	6.45" x 2.7"